
# **CENTURY+ SERIES**

Century+ series is designed with a larger interface seal than what is used in the PeeWee series enabling it to be rated at 18 kVDC.

**RECEPTACLES** (Dimensions shown as in/mm)

#### 178-9472


- Mating Torque: 5 to 6 in-lbs
- Panel Mounting Torque: 8 to 10 in-lbs



#### Ceramic-to-Metal Brazed, Hermetic

#### 178-7541

- Sealed for 1 ATM differential pressure
- Max. Leak Rate: 1x10<sup>-8</sup> cc/s He @1 ATM differential pressure




### **CABLE ASSEMBLIES**

### Single-Ended, Shielded

#### 178-9482

pressure


• Uses Wire 167-8726



# **Double-Ended, Shielded**

# 178-9483

• Uses Wire 167-8726



# **SERIES SPECIFICATIONS**

(• = Same value as above)

Series	Voltage Rating (kVDC)	Altitude Rating (ft)	Operating Temp. (°C)	Current Rating (Amp)	Receptacle Insulator Material	Plug Insulator Material	Coupling Style			Recept. Contact Material/Finish (Pin)		Wire Insulation	Braid Termination	Test Voltage @ 70,000 ft	Test Voltage @ Sea Level
CENTURY+	18	70,000	-55 to 125	5	Plastic or Ceramic	Plastic	Threaded	CRES	BeCu/Au with CRES Hood	Brass/Au or Kovar™	Shielded	FEP	Band	25	N/A

# **WIRE SPECIFICATIONS**

Part	Operating Voltage (kVDC)	Conductor			Insulation		Shielding			Jacket		Impedance	Attenuation dB/100 ft @	Capacitance pF/FT (Nom.)
Number		AWG	Strands	Plating	Material	ø in./mm	AWG	Plating	ø in./mm	Material	ø in./mm	Ω	400mhz	@1k HZ
167-8726	25	22	19/34	SPC	FEP	0.100 / 2.54	36	SPC	0.120 / 3.05	FEP	0.145 / 3.68	50	N/A	29.3

<sup>\*\*</sup>Cable Assembly Ordering Information: All cable assembly cable lengths are to be specified in inches only. For example, to order part number 178-6027 with a cable length of 10 feet 8 inches the cable assembly part number would be specified as 178-6027-128N

<sup>•</sup> Note: Product numbers and specs subject to change without notice. • Products listed represent only a small selection of Teledyne Reynolds' products please visit www.teledynereynolds.com for the most up to date product information. • Contact Teledyne Reynolds' Engineering to discuss custom designs. WARNING: Connectors should NEVER be handled mated or unmated when voltage is applied. Kovar is a registered trademark of the Carpenter Technology Corporation.